

Urano handheld CB-radio

Description:

Squelch sensitivity: min. 0.2 μ V - 120 dBm/max 1 mV - 47 dBm

Supplied with: rechargeable battery pack lithium-ion battery 2200 mAh / 7.4 V, wall charger, 20 cm antenna TNC, belt clip and user manual in English and Italian

URANO, HANDHELD CB TRANSCEIVER 40 CHANNEL AM / FM

Multistandard

Auto Squelch (ASCP).

Large multi-function LCD display with backlight.

Channel display or relative frequency.

Channel selector switch Up / Down.

S Meter.

Scan function.

Roger Beep.

Dual watch.

Channel 19 emergency pre-set.

Switch High / low power.

Keypad lock.

Socket for external microphone / speaker connection with 2,5 / 3,5 mm mono

Technical information

Frequency range: 26.965 MHz ~ 27.405 MHz (40 channels)

Power supply: 7.4 Vcc

Dimensions / Weight H x W x D : 120 x 54 x 35 mm/0.36 kg (with battery)

Frequency tolerance: \pm 200 Hz

RF Power: 1~3 W AM / 1~4 W FM

Audio response: 300 Hz ~ 2.5 kHz

Adjacent channel power: < 20 μ W

Absorption: 1.8 A (with modulation)



www.rj-elektro.fi